



Wired & wireless Compatible Intelligent Burglar Alarm Control Panel



- + For Projects Installation, 16 Wireless zones +8 Wire
- + Including 7 kinds of arming modes: single zone arming, certain time arming, outside arming, peripheral arming, overtime arming, long-distant arming, compulsory arming.
- + Including 5 kinds of disarming modes: single zone disarming, password keyboard disarming, long-distant disarming, receiving signal to disarm, use the remoter to disarm.
- + Can be programmed to carry out a variety of settings
- + In order to improve the safety, there is 1 ground 6-digit master password and 15 sub-grounds password can be set up on-demand
- + Can set up 6 grounds alarm telephone number (the fix telephone number or mobile phone) and 2 grounds alarm centre telephone number.
- + Built-in voice module can be recorded in 10-20 seconds of voice, voice alarm.
- + The control panel has the function of rush alarm, even the telephone line is using , it will never fail to report the information
- + The use of high-speed digital communications, compatible with Contact ID,4+2,SL digital Communication protocol, to alarm centre to send the alarm information
- + The control panel can be built-in DC12V/74AH Rechargeable batteries, To ensure that the shutdown does not power

FST-LFXXF8	
Power Supply	AC220V+10%
Static Current Consumption	≤ 100Ma
Power	< 1.5W
Sensor Output	Above 400mA, 12V
Current Output	DC 12~15V
Wireless Frequency:	315MHz/MHz
Environment Temperature	10°C ~55°C
Humidity	40%~70%
Weight	2.5KG
Dimension	26.5 x 26 x 7.8 cm